



DIESEL 10000 A XL - STAND BY

PORTABLE POWER

GENERATING SET Range DIESEL

PRODUCT ADVANTAGES

- Generating set guaranteed 3 years
- KOHLER air-cooled industrial engine
- Electric starter with batteries without maintenance
 - Connection interface equipped with an hour meter
- Large Autonomy

The APM202 control panel displays overspeed, starting failure, oil pressure, battery and temperature OIL SAFETY Thanks to this functionality, the engine will not start or will stop during its functioning if the oil level for gasolines or the oil pressure for diesels is too low : your generating set is perfectly protected !

Range DIESEL

Both long run times and very long life for professional applications.

DIESEL 10000 A XL - STAND BY

GENERAL SPECIFICATIONS

Range	DIESEL
Frequency (Hz)	50 Hz
Max power (kW) *	9
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Diesel Fuel
Tank (L)	35
75% cons. (l/h) *	2.10
75% Autonomy (h) *	16.70
Sound power level guaranteed LwA dB(A)	109
Acoustic pressure level @1m in dB(A)	95
Acoustic pressure level @7m in dB(A)	80

ENGINE SPECIFICATIONS

Engine brand	KOHLER
Engine type	KD425-2
Engine Type	Diesel O.H.V.
Start	Electrical
Oil shutdown	Oui
Displacement (cm3)	851
Oil system capacity including filters (l)	2.60

ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 230V 16A socket - circuit breaker + 1 230V 32A socket - circuit breaker + hour meter + indicator + APM202

DIMENSIONS AND WEIGHT

Length (cm)	89.50
Width (cm)	57
Height (cm)	77
Dry Weight (kg)	162

PACKAGING

Packaging type	Box / Pallet
Length (cm)	91
Width (cm)	58.50
Height (cm)	92
Weight (kg)	175
Pallet type	
Number of box by pallet	0
Pallet height (cm)	0
weight of the packaged Pallet (kg)	0




3/15/2022

DIESEL 10000 A XL - STAND BY - PORTABLE POWER - GENERATING SET DIESEL

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. *ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com



ACCESSORIES SUPPLIED



User and maintenance manual

OPTIONS



R02B

This set includes a differential switch, a hour meter, the plugs and a thermal circuit breaker.



RSTART2

Remote control in order to start or stop the generating set until a distance of 50 meters (needs the APM202 control panel)



VERS050

Switches over automatically if the mains fails, 40A or 100A 1P or if the mains fails, 25A or 40A 3P (needs the installation of a APM202 control panel). Includes the battery charger.



R05M

The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.



RKDS3

Maintenance kit for KOHLER KD425-2 engine.



RAP

The adaptor for industrial sockets is used to connect 230-V appliances to the industrial socket.



RH2

Cover for SDMO 's generating sets, welding sets and water pumps



RPM

Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V